
Rational numbers (4)**P26141_en**

Using the procedures done in the exercises , and , your task is to write a program that reads a sequence of rational numbers and operations

$$r_0 \quad o_1 \quad r_1 \quad o_2 \quad r_2 \quad \dots \quad o_{n-1} \quad r_{n-1} \quad o_n \quad r_n \quad ,$$

and prints the result after each operation.

Input

Input consists of a line with an initial rational, followed by a sequence of lines, each one with a pair operation/rational. As in the exercise , each rational is given by a pair of integer numbers, the second integer is not zero. The operations can be "add", "subtract", "multiply" or "divide". In this last case, the second rational is not zero.

Output

Your program must print the initial rational, followed by the accumulated result of each operation. Each rational number must be in a different line.

Sample input 1

```
1 2
add 5 2
subtract 2 1
multiply 10 1
divide 3 1
```

Sample output 1

```
1/2
3
1
10
10/3
```

Sample input 2

```
3 -6
subtract 0 5
add -2 -4
divide 1 1
```

Sample output 2

```
-1/2
-1/2
0
0
```

Problem information

Author : Salvador Roura

Translator : Carlos Molina

Generation : 2024-04-30 17:58:29

© Jutge.org, 2006–2024.

<https://jutge.org>